

Docking Stations & Accessories

Pistol Grip

For frequent scanning, **Pistol Grip** provides more ergonomics and safe handling of the Communicator. Its Safety Lock is designed to allow easy attachment & removal, and at the same time to prevent accidental release of the Pistol Grip from the H42 Communicator during operation. Action Key can be programmed to activate any function demanded by the user.

Target Solutions - All Scan-intensive Jobs

- In-Store Retail
- Warehousing
- Access Control
- Manufacturing (material flow, inventory control)

Enhancing ADC Efficiency

- easy beam aiming
- convenient holding
- safe grip/holding

Removable or Permanently Mounted

- easy attachment and removal using Safety Lock
- can be permanently mounted to the Communicator


Programmable Action Key

Pen Stylus

- always at hand, securely placed in the handle

Charging of the Communicator

- through Power Connector



Physical Characteristics		
Dimensions	152 x 69 x 134 mm	(5.93 x 2.7 x 5.23 in)
Weight	118 g	
Action Key		
Free Programmable	via H42 SDK	
Power		
Input	5 VDC ± 5%; max. 3 A	
TC Power Supply Adapter	110/230 VAC	
TC CL Adapter	12/24 VDC	

For more information contact sales@gotive.com or visit www.gotive.com

In continuing effort to improve our products, Gotive a.s. reserves the right to change designs and specifications without prior notice. Gotive is a registered trademark of Gotive a.s. Microsoft, Windows, Windows CE.Net, ActiveSync are trademarks of Microsoft Corporation in USA and/or other countries. Other product and company names mentioned herein may be trademarks of their respective owners. Copyright © 2005 www.gotive.com All rights reserved. No part of this project may be reproduced by any means without written permission of its authors. GO 032 02 02 EN 311005